User Manual bidirectional Multifunctional-Counter





Part-No. 2 772 083 englisch; 05/2011 Original language German English translated from German

Table of Contents

1	General Information	7
	1.1 Information about the Operating Instructions1.2 Explanation of symbols	:
	1.3 Limitation of Liability	9
	1.4 Copyright protection	10
	1.5 Guarantee conditions	10
	1.6 Customer Service	10
2	Safety	1
	2.1 Intended Use (Proper Use)	1
	2.2 Assembly, connecting, programming	1:
	2.3 Responsibilities of the machine/plant manufacturer	
	and operator	14
	2.4 Staff-related requirements	1
	2.5 Special hazards	1
	2.6 Safety devices	1
3	Setup and Operation	18
	3.1 Dimension Sheet / Multifunction Counter Installation	19
	3.2 Connecting the Multifunction Counter	19
	3.3 Display	2
	3.4 Keyboard functions	2
	3.5 Overview of Operating Elements	2
	3.6 Programming the Standard Function	2
	3.7 Programming the Function Codes	2
	3.8 Programming the Preset Modes	2
	3.9 Prescaler Programming	29
	3.10 Programming the (User) Times	30
	3.11 Output of ID Data	3
	3.12 Adjusting the intensity of the backlight	3

Ιā	able of Contents			rable of Content
4	General Description of Multifunctional Counter	33	10 Technical Data	111
5	Pulse Counter	38	11 Transport, Packaging, Storage	118
	5.1 Description of Pulse Counter	38		
	5.2 Signal diagrams – counter input signals	39	12 Maintenance and cleaning	118
	5.3 Signal diagrams – counter output signals	41	_	
	5.4 Programming the counter function codes	43	13 Malfunctions	119
6	Tachometer	55	14 Spare Parts	12
	6.1 Tachometer description	55	14 Spare raits	12
	6.2 Signal diagrams - tachometer	56	1E Dismontling and Disposal	101
	6.3 Programming the tachometer function codes	57	15 Dismantling and Disposal	121
7	Timer	66	16 Ordering Information	122
	7.1 Timer description	66		
	7.2 Signal diagram – timer input signals	68	17 Accessories and spare parts	123
	7.3 Signal diagrams – timer output signals	69		
	7.4 Programming the timer function codes	70		
8	Shift Counter	83		
	8.1 Shift counter description	83		
	8.2 Scroll between Total Sum and Partial Sums	84		
	8.3 Signal diagrams – shift counter input signals	84		
	8.4 Signal diagrams – shift counter output signals	85		
	8.5 Programming the shift-counter function codes	86		
9	Batch Counter	97		
	9.1 Batch counter description	97		
	9.2 Signal diagrams – batch counter	98		
	9.3 Programming the batch counter function codes	98		

General Information

General Information

1.1 Information about the Operating Instructions

These operating instructions provide important information about the handling of the multifunctional counter. To ensure safe operation it is vital that the safety information and instructions be strictly observed.

For Counters with interfaces Tico 773 and Tico 774 please see the amendment 0 773 001

The multifunctional counter has been designed for industrial use and for installation in machinery or industrial plants.

The manufacturer of the machine/plant in which the multifunctional counter is used has to ensure that the function of the counter is properly described in the Operating Instructions of the machine or plant, and that the description is in accordance with manufacturer's programming functions.

The manufacturer's safety rules shall be applicable.

In addition, the local regulations concerning the prevention of accidents and general safety information applicable to the machinery/plant shall be adhered to.

Before starting any work on the machine/plant, the operating instructions and in particular, the Safety chapter and the respective safety information must be fully read.

These operating instructions are an integral part of the product and must be maintained in the direct vicinity of the machine/plant and in a place that is readily accessible for the operating staff.

These operating instructions contain important information concerning the installation, connection and programming of the multifunctional counter.



General Information

Description of the programming sequence:

- Programming of the basic functions
- Programming of the function codes
- Programming of the user times
- Programming of the prescaler
- Programming of the presettings

Before starting to run the machine/plant, all functions that are not allowed to be changed by the operator have to be blocked.



The executed programming functions have to be documented.

1.2 Explanation of symbols

The warnings in these operating instructions are designated by symbols. Signal words at the beginning of the warnings indicate the severity of a safety hazard.

These notes have to be observed by all means, and all actions have to be taken with utmost care so as to prevent any accidents or damage or personal injury.



Danger!

This warning indicates a direct safety hazard, which may lead to serious injuries or even death if preventative action is not taken.



Warning!

This warning indicates a possible safety hazard, which may lead to serious injuries or even death if preventative action is not taken.

General Information



Caution!

This warning indicates a possible safety hazard, which may lead to minor damage or injuries if preventative action is not taken.



Note!

This symbol indicates a potentially hazardous situation, which may lead to damage to property or to the environment if preventative action is not taken.



Tips and recommendations

This symbol is used to point out to useful tips and recommendations and information ensuring efficient and trouble-free operation.

1.3 Limitation of Liability

The information and notes contained in these operating instructions were gathered in accordance with the applicable standards and regulations, the state-of-the-art, as well our long-standing experience and know-how.

The manufacturer shall not assume any liability for damage caused by:

- Non-adherence to the operating instructions
- Improper use
- Employment of unskilled or untrained personnel
- Makeshift changes or manipulation
- Opening of the multifunctional counter

As a result of special design versions, special ordering options or the latest technical developments, the actual scope of delivery may deviate from the scope described and illustrated here.

General Information Safety

1.4 Copyright protection

The operating instructions must be treated confidentially and used exclusively by the personnel responsible for the setup, maintenance, repair and operation of the machine/plant. Disclosure of these operating instructions to any third parties shall not be permissible without the prior written consent of the manufacturer.

01

The data and information stated here, including text, drawings, images and other illustrations, are protected by copyrights and subject to industrial property rights. Any misuse of such information shall be subject to prosecution.

1.5 Guarantee conditions

Our guarantee conditions are available for download from our homepage at www.hengstler.com – DOWNLOAD – General Terms & Delivery Terms.

1.6 Customer Service

Our customer service is available to provide technical information and assistance for our customers. Detailed information on your responsible contact partner is given on our homepage (www.hengstler.com) under Contact and How to find us.

2 Safety

This section provides an overview of all the important safety-relevant aspects to ensure best possible protection of the operating personnel as well as safe and trouble-free operation. Non-adherence to the instructions given in this manual may result in considerable safety hazards.

2.1 Intended Use (Proper Use)

The multifunctional counter is exclusively designed and constructed for the intended use and purposes described here.

The multifunctional counter serves together with a corresponding sensor for the counting of piece numbers, lengths, flow rates, velocities and times, as well as for the controlling and monitoring of machinery and equipment by sending control signals.



Warning!

Safety hazards due to improper use / misuse! Using the multifunctional counter for any purposes other than the ones described within the scope of intended use may cause hazardous situations. Claims for damages resulting from any kind of misuse shall be expressly excluded.

HENGSTIER 10 11 HENGSTIER

2.2 Assembly, connection, programming

These multifunctional counters are built and tested in accordance with IEC/EN 61010–1, Protection Class II – Safety Measures for Electronic Measuring Equipment. They have left the factory in a condition that is in compliance with all safety-relevant requirements. In order to maintain this condition and ensure operational safety, the User is requested to observe the safety notes and warnings given in these operating instructions!



Danger!

Risk of safety hazards due to incorrect/faulty assembly and connection.

- The max. operating voltages must not be exceeded!
- 12 24VDC and 24VAC multifunctional counters have to be operated at safety extra-low voltages (SELV) and under potential-compensated conditions in order to prevent hazardous shock currents.
- An external fuse has to be provided to protect the multifunctional counter (see Chapter 10, Technical Data).
- Installation and assembly shall be carried out by skilled and trained electricians only.
- Do not connect the multifunctional counter without making sure that it no longer carries any live voltages. Always separate it from the mains supply before connecting.
- Make sure that live terminals are properly protected against inadvertent contact.
- To ensure proper protection of terminals against hand contact, make sure that the live conductors are properly connected to the terminals.
- It's not allowed to use the multifunctional counter outside of the specified temperature range. If neccessary appropriate precoutions have to be applied

(e.g. air ventilation). • The rules and regulations set forth by the local electricity providers have to be observed.

- Do not establish any connections with non-allocated (NC) terminals.
- Multifunction counters may only be operated in a properly installed condition.
- If safe operation seems to be impaired, make the multifunctional counter inoperable and secure it against inadvertent operation.
- Scope of applications: industrial processes and controls. Overvoltage across
 the terminals must be limited to the values of overvoltage category II.
- The installation and wiring environment has considerable impact on the electromagnetic compatibility of the multifunctional counter. Therefore, electromagnetic compatibility of the entire plant has to be ensured during the installation.
- In areas presenting the risk of ESD (electrostatic discharge), make sure to use ESD-protected plugs and switches during the installation.
- If the functions "prescaler input", "preset input" and "key reset" are not allowed to be used by the machine/plant operator, access to these functions must be blocked for machine operators. Depending on the machine/plant design or concept, non-permissible input may impair the operational safety and function of the machine or plant.



Danger!

The manufacturer of the machines / plants has to ensure, that no risks result from this.

 The machine/plant manufacturer shall be responsible for the preparation of operating instructions / plant description including the following: Safety

Safety

- Description of functions according to the programming of the multifunction counter:
- Description of the settings to be adjusted by the machine/plant operator;
- Information concerning the occupational safety requirements and possible hazards arising from the operation of the machine/plant.

2.3 Responsibilities of the machine/plant manufacturer and operator

Multifunctional counters are designed for installation in machines/plants. Therefore, the manufacturer and operator of the machine/plant are subject to the legal obligations concerning occupational safety and health.

Besides the safety notes given in these operating instructions, the relevant rules and regulations concerning safety and the prevention of accidents, and the applicable environmental requirements have to be met. In particular:

- The machine/plant manufacturer shall be obligated to ensure that all the requirements mentioned in section 2.2 be fulfilled during the assembly, connection and programming.
- The operator shall obtain all the required information about the applicable
 occupational safety rules. In addition, the operator shall be obligated to
 prepare a risk assessment of possible hazards that may arise due to the special working conditions at the place of installation of the machine/plant.
 This risk assessment shall be documented in the form of operating instructions for the machine/plant.
- Throughout the entire operating time of the machine/plant the operator shall be obligated to check if the operating instructions prepared are in accordance with the latest status of requirements and, if required, make the appropriate adjustments.

- The operator shall ensure that all staff members who are involved in the machine/plant operation have read and fully understood these instructions. Moreover, the operator shall be obligated to train the operating personnel at regular intervals and inform them about any potential hazards.
- The operator shall ensure that the operation and cleaning of the machine/ plant is exclusively carried out by skilled and trained personnel.
- The operator shall ensure that all maintenance and repair work shall only be carried out by skilled and trained personnel.

2.4 Staff-related requirements



Warning:

Danger of personal injuries if handled by insufficiently qualified staff! Improper handling may cause severe personal injuries and damage to property.

- Actions requiring special skills have to be carried out only by the personnel designated in the appropriate sections of these instructions.
- Keep unqualified personnel away from hazard areas.

The following staff qualification requirements have been defined for the various scopes of activities:

Instructed personnel

These persons have been instructed by the operator with regard to the tasks assigned and the potential hazards caused by improper handling.

Skilled personnel

Due to their educational and professional skills, know-how and experience, as well as due to their knowledge of the relevant regulations, these persons are capable of executing their assigned tasks and recognize potential hazards independently.

Safety

Skilled and trained electricians

Due to their educational and professional skills, know-how and experience, and due to their knowledge of the relevant regulations in the field of electrical engineering, these persons are capable of executing electrical work and recognizing potential hazards independently.

2.5 Special hazards

This section indicates certain residual risks, which may arise as a result of the risk assessment

The safety information and warnings given here and in the following chapters of these instructions have to be observed in order to reduce any health hazards and avoid hazardous situations.



Electric current

Danger!

Lethal hazard of electric shock!

Any contact with hazardous live components presents a direct lethal hazard.

Damages of the insulation or individual components present a potential lethal hazard.

- In the event of any damage to the insulation, immediately disconnect the voltage supply and initiate the appropriate repair work.
- Any work on the electrical plant has to be carried out by skilled and trained electricians only.
- Before commencing your work on the electrical system, disconnect it from the main supply and check that it no longer carries any live voltages.

- Prior to conducting any maintenance, cleaning or repair work, disconnect the mains supply and secure it against inadvertent switching on.
- Do not short-circuit or make fuses inoperable.

2.6 Safety devices



Warning! Lethal hazard by non-functional safety devices! Safety devices are provided to ensure a maximum of operational safety.

The multifunctional counter itself does not include any installed safety devices.

These safety devices have to be attached externally.

Protect the electrical supply of the multifunctional counter by means of external fuses (see Chapter 10, Technical Data).


Whether or not additional safety devices (e.g. emergency-off buttons) have to be provided depends on the general design and construction of the machine or plant.

The machine/plant manufacturer shall be responsible for providing such additional safety devices in according with his own risk assessment.


- Display
- Operating keys
- Flat gasket
- Bracket
- Enclosure
- Plug for DC or sensor supply; Electronic inputs and outputs
- Connection terminal AC supply and relay contacts
- Circuit diagram 8



Dimension Sheet / Installation of Multifunction Counter



3.2 Connecting the Multifunctional Counter



VDC 2 relays / 2 transistors

VDC 1 relay / 2 transistors

VAC transformer 1 relay / 2 transistors

VAC Trafo 2 relays / 2 transistors

1 Sensor 24VDC max115mA	No 16
2 ov	NG 15
3 Input A	NC 14
4 Input B	Out Rel 2 13
5 Input C	30VDC—'SA 124
6 Application input/out	p. niax 250V 11 →
7 OUT1_Tr, 24VDC/50r	nA AC-Supply 10→ 100-240V ≈
8 QUT2_Tr, 24VDQ/50n	nA extern. Fuse 9-
	حنے

VAC switching power supply 2 relays / 2 transistors

VAC switching power supply 1 relay / 2 transistors



The plug has to be disconnected from the counter before the cables are fastened by means of screws or screw-type terminals.



It is not allowed to contact the encoder to a direct current line voltage without protective circuit for EMC. For cable lengths > 30 m a protective circuit is always necessary!

When programming the input level to TTL an additional protective circuit is necessary.

We recommend the installation in an metallic environment.

Only valid for DC-Versions:

When switching on the device in PNP-Mode, a short signal is applied to inputs A,B,C and the application input.

To suppress the pulse in TTL-Mode each input has to be connected to a resistor of 10 kOhm/0,125W against OV.


When switching on the device a short signal is applied to the application output.

This pulse, if needed, is possible to suppress by connecting a resistor of 10 kOhm / 0,225 W against 0 V to the application-output.

3.3 Display

After switching on, all segments and characters are illuminated for approx. 2 seconds; then the display changes over to the Display or Programming Mode.

The display is available in five different versions:
Reflectiv: black figures on bright reflecting background
Transflective positive: black figures on back lighted ground
Transmissive white: white figures on black ground
Transmissive red: red figures on black ground
Transmissive green: green figures on black ground



During the Programming of Function Codes

. 5	<u> </u>		
Е			
Enter - Key	UP - Key	Down - Key	SHIFT - Key

Programming

If pressed together with POWER ON (keep keys pressed and switch on the device)

E + 📤	Selects standard functions
E + 🕶	Sets function codes
E +)	Selects ID data (Article code (ID No.), manufacturing date, serial number,)
+	Sets User Times

During the Programming of Function Codes

+ -	Display of function code Switches between function code text and function code number
-----	---

During Operation

+ -	Reset
E + •	Sets preset 0
E + 🕶	Sets preset 1
E + 📤	Sets preset 2
+	Sets prescaler

Setup and Operation


Switches between total sum and partial sums and/or
count value and totalizer or batch counter

Additional function for timers

Additional function for timers			
	Timer start (If enabled with function code F15)		
—	Timer stop (If enabled with function code F15)		
Additional function backlight versions			
	Go to the adjustment menu (pressing > 5 s)		
Adjustment of the intensity (brighter or darker)			
Е	Save and going back to display mode (Pressing within 15 s)		

23

3.5 Overview of Operating Elements




Setup and Operation

3.6 Programming the Standard Function

The device described here is a multifunctional counter, which can be programmed for a variety of functions, i.e. pulse counter, tachometer, timer, shift counter or batch counter functions. The first step is to set the standard function (the factory setting of the device is the "pulse counter" setting).

Now continue with the programming of the function codes (Chapters 5-9) or User Times (Chapter 3.10)



Function code Fn, Display Row 18 18 18 18 18 18

Function	No.	Display Row 2	
Setting of Standard	0*	888588	Pulse counter
Function	1	8.8.8.8.8	Tachometer
	2	8,8,8,8,8,8,	Timer
	3	58888	Shift Counter
	4	688888	Batch Counter

3.7 Programming the Function Codes

The function codes (system parameters) are used to program the function and behavior of the inputs and outputs, as well as the behavior of the device in its adjusted basic mode. The detailed selection options are described in Chapters 5 to 9.

Programming mode	Change function setting	Save and change to next function code	Save and change to counter operation
E + 🔻	or 🔽		Е
Keep pressed and switch voltage on simultaneously	press	press	press

Change between Text Display and Numerical Display



In the function code Programming Mode, the first row shows the name of the function code in the form of text (7-segment display). The second row shows the selectable option in a text form, too. By simultaneously pressing the Up and Down buttons, the display in the first row changes to a numerical display; after pressing these buttons once again, the display in the second row also changes to a numerical display. Pressing these buttons for a third time reverts both rows to the text display again.

Setup and Operation



Attention: With each change among text and numeric display, the currently activated function code will return to the factory setting and may have to be readjusted.

The factory setting is designated with an asterix *.

3.8 Programming the Preset Values

By simultaneously pressing the E + Up, E + Down or E + Shift key you can change to the Preset programming mode:

Use the shift key in the programming mode to change a setting position. The selected position will start to flash. Use the shift key again to move by one position to the right. Then use the UP or Down key to increment or decrement the position by 1.

Rule for the 6th position: The change from 9 to 0 or 0 to 9 is indicated by a changing prefix.

Use the E key to leave the programming mode and return to the display mode. Your entries will be saved.

On leaving the programming mode, the presets are tested for attainability and recalculated, if necessary, because not all the values may be attained at a prescaler value of >1. The presetting is then rounded to the next attainable value.

If no key is pressed for more than 16 seconds in the programming mode, the counter will automatically return to the display mode. In this case, however, no entries will be saved except the last value saved with the E-key.

Set the preset value to 0 by pressing Up and Down keys simultaneously.

Programming mode	Position flashes:	Set position:	Save and return to display mode
E + 📤		▲ or ▼	Ε
Preset 2	press	press	press
E + Preset 1		+	Zero in
E +)			Set Preset
Preset 0			

Setup and Operation

3.9 Prescaler programming

By pressing the Up + Shift keys simultaneously you can change to the Prescaler Programming Mode.

In the Programming mode, the position to be changed is selected by means of the shift key. The selected position will start flashing. Use the shift key again to move by one position to the right. Then use the UP or Down key to increment or decrement the position by 1. It is not possible to save a value of 00,0000. In this case the system will save 01,0000.

Use the E key to leave the programming mode and return to the display mode. Your entries will be saved

On leaving the programming mode, all the presets are recalculated because not all the values may be attained with a prescaler value of >1. Therefore, the presets have to be checked and corrected as necessary after saving the prescaler.

If no key is pressed for more than 16 seconds in the programming mode, the counter will automatically return to the display mode. In this case, however, no entries will be saved except the last value saved with the E-key.

Press the Up and Down keys simultaneously to set the prescaler to 01,0000.

Programming mode	select a position: (starts flashing)	Set position	Save and return to display mode
+		▲ or ▼	Ε
press	press	press	press
			Set prescaler
+	set to 01,0000		

3.10 Programming the user times

For programming the signal time for monostable output signals, 9 fixed signal times between 0.02 s and 10 s are available. In addition, three different signal times between 0,01s and 599,99s can be set by the user. The outputs are deactivated if the setting is 0.00 s.

Programming mode	Select a position	Set position	Save and go to the next user setting; after user 3, return to dis- play mode
+		▲ or ▼	Е
Keep pressed and switch voltage on simultaneously	press	press	press


Function code Fn, Display-Row 1 \square \square \square \square \square \square \square

Function	No.	Display Row 2	
Sets the Signal	0*	858888	Signal time 1
Times	1	U.S.E.E.E.E.	Signal time 2
	2	858888	Signal time 3

Setup and Operation

3.11 Output of ID data

This function is used to retrieve ID data, e.g. article numbers and various manufacturing data.



Display row 1	Display row 2
888888	Article number
888888	Manufacturing date
5.E.B.B.B.B.	Serial number
5 B B B B R A	Software number
588568	Software release

31

3.12 Adjusting the intensity of the backlight


For counters that come with a backlight you have the possibility to adjust the intensity of their backlight.

To get into the menu of the adjustment, you have to press SHIFT for more than 5 seconds. The display then shows:



By pressing the UP or DOWN key the display gets brighter or darker.

If the E-button is pressed within 15 s, you go back to the normal counter display and the adjusted setting is saved. If the E-button is not pressed within 15 seconds, you will go back automatically to the normal counter menu without saving any made changes.



General description of multifunctional counter

4 General description of multifunctional counter

The following description is applicable for all standard settings. Special descriptions can be found in the appropriate chapters of this manual.

Factory setting (Defaults)

Sets all the function codes to the factory settings, i.e. all codes designated with * .

Prescaler (pulse metering factor):

The "Prescaler" is a multiplier. Each input pulse is multiplied by the adjusted factor. The display shows integers only. After a reset the counter is completely reset to 0: this also includes the non-visible value of < 1.

At a prescaler of >1 not all the values are selectable. If invalid Preset values are selected, the counter will round them up to the next possible value.

Example: PSC 5 cannot select (reach) Preset value 7. In this case, the counter automatically changes the Preset value to 10).

If the Prescaler is changed, this may also affect the Preset values, which may have to be changed accordingly.

Adjusting range 0,0001 to 99,9999

The Prescaler is used, for example, to convert counter pulses into meaningful units, to adapt the units of measurements (e.g. cm-pulses to inch-pulses), or to compensate for worn out measuring wheels.

Formula: PSC = Desired/nominal display / number of pulses

Example: Flowmeter 173 pulses per 100 liters; display in liters

PSC = 100 / 173 = 0,5780

Example: 1 pulse per cm; display in inch

PSC = 1 / 2,54 = 0,3937

General description of multifunctional counter

Attention: This is only valid for counters and tachometers. For timers please refer to the special Timer Description.

Display 2. row:

The display of the 2nd row can be programmed as follows: P 2, P 1, P 0, Prescaler, Batch counter, totalizer or partial sums (shift counter)

Counter and control inputs:

The counter is fitted with 3 counter and control inputs and, in addition, with an application input (see below). These inputs are assigned various counter or control functions by means of function code settings

Input logic:

The input logic can be programmed to NPN or PNP, each at the 8V-level or TTL level; see Technical Data for the switching threshold.

Reset/Set:

Manual setting via keys (lockable)
Electronic setting via control input (and/or application input)
Automatic programming after reaching the main Preselection
Programmable Power-On Reset

Depending on the function code the counter is:

1.) Reset: reset to 0

P 2 is the main Preset (preselect) value

During unidirectional counting the counter will add up.

or

2.) Set: reset to P 2
Signal 2 at 0
During unidirectional counting the counter will subtract.

For time counting, batch counting or shift counting, it is possible to reset partial sums or the total sum, batch counter or 2nd totalizer individually or at the same time via the application input.

General description of multifunctional counter

Independently the counter can be reset to Preset value 0 via the application input (see below).

Exception: Tachometers do not have a reset/set function

Static/dynamic reset:

Static reset: Reset over the entire pulse width of the reset pulse

Dynamic reset: Reset via the active edge; thereafter, counter operation is

possible independently of the pulse width of the reset pulse.

Exception: Tachometers do not have a reset/set function

Teach input:

Using the Teach Input (application input) the counter status is imported in Preset 2

Decimal Point:

The decimal point is only an optical reading assistence on the display and does not change the value. For example, for a value of 1 pulse per cm, the setting 0.00 makes it easier to read the value in m and cm.

Exception: This does not apply to tachometers and timers. Please refer to the detailed Tachometer and Timer descriptions.

Input damping (Attenuation)

The inputs A and B are limited to 60 kHz. The Application Input is limited to 6 kHz.

Following maximum input frequencies are not to be exceeded:

Phasediscriminator single evaluation: A and B each 30 kHz (TTL 15 kHz) Phasediscriminator double evaluation: A and B each 30 kHz (TTL 15 kHz) Phasediscriminator quadruple evaluation: A and B each 15 kHz (TTL 15 kHz) Unidirectional counting and directional input: Input A 60 kHz (TTL 15 kHz) Differential counting, summation (totalizing): Input A + B 60 kHz (TTL 15 kHz)

General description of multifunctional counter

When the application input is used as an additional count input, the above mentioned input frequencies have to be reduced by the frequency of the application input:

If mechanical contacts are triggered (i.e. relays, switches, Reed contacts, etc.), the input frequency has to be damped (attenuated) to 30 Hz, so as to filter out bounce pulses.

If damping to 30 Hz is selected, all inputs can be used at 30 Hz.

To reach these values the amplitude thresholds are to be hold. (See technical data – chapter 10)

Signal

P 1 and P 2 are available as relay changeover contacts and electronic output signals (PNP).

P 0 is available as an electronic output signal across the application output (PNP).

If a signal is active, this will be shown on the LCD display. Optionally, the multifunctional counter can be set to have the display flash if one or all the preset values are acive.

This is also valid for Preset 0 (if no output has been assigned)

Signaltime:

- 1.) bistable: Cleared by electronic or manual reset.
- P 0 + P 1= bistable additionally cleared by signal 2
- Attention: Signal 2 must not be bistable for automatic reset.
- **2.) monostable:** Up to 9 fixed signal times are available between 0,02s and 10s. In addition, user times can be programmed between 0,01s to 599,99s.
- **3.)** Range signals: active as long as the counter reading is within the adjusted range.

Signals active on/off

During normal operation the relay is energized if the signal is active. This behavior can also be inverted (also applicable to the transistor outputs).

General description of multifunctional counter

Application input/output:

Depending on the standard function, up to 11 (eleven) functions can be assigned to the application input/output. Note, however, that only one of these functions can be selected.

Further details are given in the Function Code Chapter.

Application - Set to preset 0

Programs the application input to act as a Set Input. The counter is set to Preset 0, independently of the reset via input C or the keyboard.

This function is not available for tachometers.

Application keylock:

All keyboard functions can be locked (latched) individually (Reset, P 0, P 1, P 2, Prescaler)
Lock mode: release after 10s, complete keylock or keylock depending on keylock input (application input)



Our advice! After setting up the system, lock (latch) all the keyboard functions that are not allowed to be changed by the user.

IFNGSTI FR 36 37 HFNGSTI FF

Pulse counter

5 Pulse Counter

5.1 Description of the Pulse Counter

(Supplementing the General Description in Chapter 4)

Counter mode:

The following counter modes can be selected:
Unidirectional counting, adding or subtracting;
Unidirectional counting with directional input;
Differential counting, summation (totalizing) or
phase discriminator (quad) with single, double or quadruple evaluation.

Output signals mode of operation:

- **1.) coincidence signal:** The counter operates in the coincidence mode, i.e. output signals are activated after reaching the Preset value for the programmed period of time.
- 2.) Trail: P 2 and P 0 are under coincidence operation; they operate as described in item A.

P 1 is the trail. P 1 is not absolute to 0, but relative to P 2.

If the setting is F8=1, the following will apply:

Signal 1 is returned at P 2 - P 1

Example: P 2=1000, P 1=200, Signal 1 at 800;

If P 1 is negative: P 2=1000, P 1=(-200), Signal 1 at 1200

If the setting is F8=2, the following will be applicable:

Signal 1 is returned at P 2 + und - P 1

(Example: P 2=1000, P 1=200, Signal 1 at 800 or/and 1200)

3.) range signal: VW 1 and 2 are range signals: Signal 1 is active at a counter reading < P 1 and Signal 2 is active at a counter reading > P 2

Intermediate cut:

Depending on the application it may become necessary to isolate the main signal during the reset, e.g. when the first material lengths or certain lengths showing material defects have to be cut on length-cutting systems.

Additional totalizer (summation counter)

The additional totalizer sums up all values, even if the main counter is continually reset. The shift key can be used to switch between the counter reading and the total sum. The totalizer can only be reset manually.

To do this, select the total sum from the first row; then press the reset keys.

Prescaler Output PSC-out:

The prescaler output is an application output.

With each increase of the counter reading the number of output pulses corresponds to the respective number of increments.

The pulse length of the prescaler output corresponds to a frequency of 500 Hz.

When using the prescaler output the max. count frequency is:

F max = 500 / PSC.

So it is possible that the maximum input frequency can not be reached.

Application counter input add / sub

The application input may be assigned to the Count Up or Count Down function.


This is a counter input, which is available in addition to the counter mode adjusted with F1.

Application Latch/Reset

Latch/Reset is an application input. If the counter is reset via the application input, the counter reading is held constant. The counter continues to remain fully functional and operates in the background mode. During the next reset the current (updated) value will be shown on the display.

5.2 Signal diagrams input signals (PNP-Logic)

Unidirectional counting (F1 = C G r) = 0



Directional input(F1= C d r) = 1

Input A

Directional input (F1= C d r) = 1

Input B

Directional input
Input B


Directional input
Input C


Reset
Counter reading 1 2 3 2 3 4 0 1

Differential input (F1= A S r) = 3

Input A








5.3 Signal diagrams - Output signals


Output signals monostable

Coincidence signals P 0 (F10), P 1 (F11), P 2 (F12) monostable



Output signals bistable

Coincidence signal time P 0 (F10) monostable P 1 (F11), P 2 (F12) bistable




Pulse counter

Trail Preset


P 0 (F10) Coincidence signal monostable, P 1 (F8+F11) trail signal, symmetrical,

P 2 (F12) Coincidence signal monostable



Range signals

P 0 (F10) Coincidence signal monostable P 1 + P 2 range signal



Pulse counter

5.4 Programming the counter function codes

Program- ming mode	Change function setting	Save and change to next function	Return to display mode
E + 🔻	▲ or ▼		Е
Keep pressed and simultaneously turn Voltage On	press	press	press
Alternative display of function codes	+ 🔽	text in row 1. By pressing both ously you can clear display (F 0 to pressing these knumber of the s	eys once again the electable options d in addition. This

Function code FO, Display Row 1: F E E E E

Function	No.	Display Row 2	
Factory Setting (Defaults)	0*	8.8.8.8.8.	No Function
	1	8.8.8.8.8.5	All Function Codes are set to the values marked with *

Function code F1, Display Row 1: 🛛 🖺 🖽 🗎 🗎

Counter	nter 0* FFFF		Input A	Input B	Input C
Mode	0"	.	Count. inpt.	Gate	Reset
	1	8.8.8.8.8.	Count.inpt.	Direction. Input	Reset
	2	9.8.8.8.8.	Count.inpt.	Direction. Input	Gate
	3	8.8.5.8.8.8.	Adding	Subtracting	Reset
	4	A.B.S.B.B.B.	Adding	Subtracting	Gate
	5	8.8.8.8.8.	Adding	Adding	Reset
	6	908888	Channel A	Channel B	Reset
	7	908886	Channel A	Channel B	Gate

Function code F2, Display Row 1: 9 11 8 11 11

Edge	0*		Single evaluation
Evaluation /Quadrat.	1	8.8.8.8.8.	Double evaluation
evaluation	2		Quadruple evaluation

Function code F3, Display Row 1: 🖽 🖺 🖺 🖺 🖺

PNP/NPN- Logic	0	пепене	NPN-8V-Level
	1*	888888	PNP 8-V Level
	2	888888	NPN TTL-Level
	3	888888	

Function code F4, Display Row 1: 🗄 🖶 🗒 🗒 🗒 💆

Input- damping	0	98888	30 Hz damping (e.g. for mechanical contacts)
(Attenu- ation)	1*	88888	F max. (see chapter 4 and 10)

Function code F5, Display Row 1: 8 5 8 8 8

Set / Re- set- Mode	0*	8.8.5.8.8.8.	Reset to 0
	1	888588	Automatic reset to 0 after reaching Preset 2
	2	5.8.8.8.8.8	Set to Preset 2
	3	858888	Automatic set to Preset 2 after reaching 0

Function code F6, Display Row 1: 4 E 5 E E B

dynam./ static Reset	0*	58888.B.	Static reset (reset as long as the signal is applied)
	1	89888	Dynamic Reset (ready to count after reset (even if reset signal is applied for a longer time)

Function code F8, Display Row 1: 8 8 8 8 8 8

Mode Preset 1	0*	8.8.8.8.8.8.	P 1 normal preset; absolute to the counter reading (coincidence signal)
	1	8.8.8.8.8.8.	P 1 as a trail preset with prefix (relative to P 2)
	2	88888	P 1 as a trail preset symmetric trail (relative to P 2)
	3	8.8.8 6.8.8.	P 1 and P 2 as a range signal (Sign.1 < P 1, Sign.2 > P 2)

Output signal		REBBA	Active On	
	1	8.8.8.8.8.8		ĺ

Function code F10, Display Row 1:5 1 1 1 1

Tunction	couc .	10, Bispidy Nov	
Signal time P 0	0	885888	Disabled / No output signal
	1	685886	Bistable, reset with Preset 2 or Reset
	2	8.8.8.8.8.	0,02 s
	3	8.8.8.8.8.5	
	4*	8.8.8.8.8	
	5	8.8.8.8.8	
	6	8.8.8.8.5.6	
	7	8.8.8.8.8.	
	8	8.8.8.8.8.	2,00 s
	9	8.8.8.5.88	
	10	8.8.8.8.8	10,00 s
	11	85555	User setting 1 (0-599,99 s)
	12	85888	User setting 2 (0-599,99 s)
	13	858888	User setting 3 (0-599,99 s)

Function code F11, Display Row 1:5 8 8 8 8

Signal time P 1

BBBB Disabled / No output signal

9 8 8 8 8 8 5,00 s

10 🗏 🖟 🖟 🖟 🖟 10,00 s

11 User setting 1 (0-599,99 s)

12 User setting 2 (0-599,99 s)

13 **USE FIRE** User setting 3 (0-599,99 s)

Function code F12, Display Row 1:5 1 5 1 5

Signal time P 2

0	88888	Disabled / No Output signal

Bistable; Reset
Cannot be used in conjunction with automatic Reset

2 0.02 s

3 8 8 8 8 8 0,05 s

4* □□□□□ 0,10 s

6 8 8 8 8 9 0,50 s

9 888**5.**00 s

10 | | | | | | | | | | | | 10,00 s

11 **Life Fig. 1** User setting 1 (0-599,99 s)

13 $\square \subseteq \square \subseteq \square \subseteq \square$ User setting 3 (0-599,99 s)

Function code F13, Display Row 1: 4 Pa Rot E

Decimal point	0*	8.8.8.8.8. 8 .	No decimal point
	1	8.8.8.8 .8 .	1 decimal place
	2	8.8.8.8.8	2 decimal places
	3	8.8.8.88	3 decimal places
	4	8.8.8888	4 decimal places

Function code F14, Display Row 1: HHHHHH

Tunetion code 111, Display now 1122222				
Display flashes	0*	888888	No flashing	
	1	8.8.8.8.8.	Flashes as long as P 0 is active	
	2	8.8.8.8 . 8.	Flashes as long as P 1 is active	
	3	8.8.8.8.8.2.	Flashes as long as P 2 is active	
	4	8.8.8.8.8.	Flashes as long as one P is active	

Display in 2nd row	0	8.8.8.8. 8.	Preset 0
	1	8.8.8.8.8.	Preset 1
	2*	8.8.8.8.8.2.	Preset 2
	3	8.8.8.8.8.8	Prescaler
	4	8.8.8.8.8.8	Totalizer

Output at Reset (In-	·	_	Do not activate Preset 2 during Reset
term. Cut	1		Activate Preset 2 during Reset

Function code F17, Display Row 1 🖁 🗓 🖫 🗒 🗒 💆

Power On (Reset)	0*	 Restore counter value
	1	 Reset at Power On

Function code F18, Display Row 1.0 0 0 0 0

Output	o 8.8.8.9.6.5		Restart signal time after power fail output switches
signal Memory	1*	8.8.8.8.8.8.	Do not restart signal time after power fail

Addtl.	0	8.8.8.9.8.5.	
Totalizer	1*	888888	Disah

Function code F22, Display Row 1:88888

Tunction code 122, Display Now 13412 2 244			
0	850000	Prescaler output	
1	8.8.8.8.8	Output Preset 0	
2		Directional output	
3*	88888	Counter input – adding	
4	88888	Counter input – subtracting	
6	6.R.E.E.B.B.		
7	8.88.8.8.8.		
	8.8.8.8.8.	Hold input (display lock)	
9	888888	T 1 1 1 1	
10	5.8.8.8.8.8.	Set input (Set to Preset 0)	
	0 1 2 3* 4 6 8	0 PSC 6 E E 1 PO BO B E 2 B B B B B B B B B B B B B B B B B	



Should you have a counter with interface, the additional function codes F24 - F27 are described in the seperate manual for the interface version.

Function code F30, Display Row 1 1 5 5 5 5 5

Lock Reset key	0*	Enable keyboard reset
	1	Keyboard reset locked / delayed

Function code F31, Display Row 1: \Box \Box \Box \Box \Box \Box \Box

Lock Preset 0	0*	 P 0 Setting enabled
	1	P 0 Setting locked / delayed

Function code F32, Display Row 1: P B B B B B B

```
Lock
Preset 1

0*

1 P 1 Setting enabled

P 1 Setting locked / delayed
```

11

888888

Latch and Reset

(Save display at Reset)

Tachometer

Function code F33, Display Row 1: 8 8 8 8 8

O* B. R. L. B. P. 2 Setting enabled

Lock
Preset 2

1 B. R. L. B. C. P. 2 Setting locked / delayed

Function code F34, Display Row 1: 95 1 0 0

Function code F35, Display Row 1: 4 8 8 8 8

6 Tachometer

6.1 Tachometer Description

(Supplementing the General Description given in Chapter 4)

Operation:

A tachometer measures the period (PNP: time from one rising edge to the next one); NPN: time period from a falling edge to the next one), and converts and displays this time in 1/sec or 1/min.

Tachometer Mode of Operation:

The following modes of tachometer operation can be selected:

Unidirectional counting;

Unidirectional counting with directional input;

Differential counting, summation (totalizing);

Phase discrimination (quad) with single, double or quadruple evaluation;

Indication of ratio A/B and

Indication of percentage (A-B) /A in %

Decimal point

Tachometer mode of operation 0-4 (function code F1)

The decimal point only serves for better legibility and does not change the value

Tachometer mode of operation 5 + 6 (function code F1)

The decimal point is included in the calculation and increases the resolution.

Output signals Mode of operation:

The tachometer uses the following limit values:

P 1 and 2 are limit (range) signals

Signal 1 is active at the displayed value of < P 1 and

Signal 2 is active at the displayed value of > P 2

Signal 0 is active at the displayed value of > P 0: (application output)

Tachometer

Tachometer

Display unit:

Programmable: 1/sec or 1/min

Using the setting 1/min and prescaler 60 the display will show 1/hour.

Min. input frequency:

Programmable 1 Hz or 0.1 Hz.

If two edges do not occur within 1 s or respectively 10s,

a value of 0 will be displayed.


Startup suppression:

Programmable Yes/No

During the startup the lower limit signal is suppressed until the lower limit value is exceeded for the first time.

The startup suppression will become active again, if the minimum frequency is fallen below.

6.2 Signal diagram - Output signals



6.3 Programming the tachometer function codes

Programming mode	Change function setting	Save and change to next function	Return to display mode
E + 🕶	△ or		Е
Keep pressed and simultaneously turn Voltage On	press	press	press
Alternative display of Function code:	A + V	The function codes text in re By pressing both k ously you can changerical display (F 0 pressing these keys number of the selection setting will be	ow 1. eys simultane- ge to the nume- to F 35). After once again the ectable options n addition. This

Function code FO, Display Row 1 5 5 5 5 5

Function	No.	Display Row 2	
Factory Setting (Defaults)	0*	8.8.8.8.8	No function
	1	8.8.8.8 8.8.	All function codes are set to the values marked with *

			Input A	Input B	Input C
Tacho mode of operation	0*	8,8,6,8,8 B	Count input	Gate	Hold (Display memory)
	1	E.B.B.B.H.B.	Count input	Direct. input	Hold (Display memory)
	2	8.6.6.8.8	Adding	subtracting	Hold (Display memory)
	3	88888	Adding	Adding	Hold (Display memory))
	4	908884	Channel A	Channel B	Hold (Display memory)
	5	8.8.6.8.8	Channel A /	Channel B	Hold (Display memory)
	6	8-6976	(A-B) / A in ^c (Difference i		Hold (Display memory)

Function code F2, Display Row 1:948888


Edge Evalua- tion/ Quadrat. evalua- tion	0*	8.8.8.8.8.	Single evaluation
	1	8.8.8.8.8.	Dual evaluation
	2	8.8.8.8. 4 .	Quadruple evaluation

Function code F3, Display Row 1:

PNP/ NPN- Logic	0	888888	NPN 8 V-Level
	1*	282 <u>1</u> 48	
	2	888888	NPN TTL-Level
	3	888888	PNP TTL-Level

Function code F4, Display Row 1: 🛚 🗔 🗒 🗒 🗒 💆

Input damping	0	88888	30 Hz attenuation (e.g. for mechanical contacts)
(At- tenuat)	1*	88888	F max. (see chapter 4 und 10)



Function code F7, Display Row 1:5 8 8 9 18

O BBBBB With startup suppression

Startupsuppress.

1* BBBBBB Without startup suppression

O* REEDE Active On

Output
signal

1 REEDE Active Off

Function code F10, Display Row 1:5 1 1 1 1 1

PO 0* 3 5 1 5 1 5 1 1 Disabled / no Output signal Addtl.
Upper limit 1 E 1 1 5 1 5 5 6 Additional range signal > PO

Function code F11, Display Row 1:5 4 5 8 8

Function code F12, Display Row 1:5 8 8 8 8

O* 日日日日 Disabled / no Output signal
P 2 Upper
limit
1 日日日日日 Range signal > P 2

Tachometer Tachometer

Function code F13, Display Row 1: 8 8 8 8 8 8

Decimal place	0*	8.8.8.8.8.	No decimal point
	1	8.8.8.8.8.	1 Decimal place
	2	8.8.8.0.88	2 Decimal places
	3	8.8.8.8.8	3 Decimal places
	4	8.8.88.88	4 Decimal places

Function code F14, Display Row 1: 8 8 8 8 8

runction code F14, Display Row 1: 11 11 11 11 11				
Display flashes	0*	888884	Do not flash	
	1	8.8.8.8.8.0	Flashes as long as P 0 active	
	2	8.8.8.8 . 8.	Flashes as long as P 1 active	
	3	8.8.8.8.8.	Flashes as long as P 2 active	
	4	888888	Flashes if one preset is active	

Function code F15, Display Row 1:2.8 8 8 8

Display in 2nd row		8.8.8.8.8.0.	Preset 0
	1	8.8.8.8.8.	
	2*	8.8.8.8.8.2	
		8.8.8.8.5.6.	

Applica- tion Input/ Output	0	8.8.8.8.8	Output Preset 0
	1	888888	Directional output
	2*	88888	Count input adding, or 2nd count input A
	3	88888	Count input subtracting, or 2nd counter input B
	4	6.R.E.E.B.B.	Gate Input
	5	H.B.B.B.B.B.	Hold-Input (display memory)
	6	8.8.8.8.8.8	Teach Input (count value becomes P 2)
	7	8,8,8,8,8,8	Keylock-Input

Tachometer



Should you have a counter with interface, the additional function codes F24 - F27 are described in the seperate manual for the interface version.

Function code F31, Display Row 1 🖁 🗒 🗒 🖥 🗸

set 0 Set-	0*	P 0 Setting enabled
		P O Setting locked / delayed

Function code F32, Display Row 1 🖁 🖁 🗒 🖥 🗟

set 1 Set-		P 1 Setting enabled
		P 1 Setting locked / delayed

Function code F33, Display Row 1: \square \square \square \square \square \square \square

		P 2 Setting enabled
ting		P 2 Setting locked / delayed

Tachometer

Function code F34, Display Row 1:85 2 2 2 2

Lock	0*	PSC Setting enabled	
Prescaler Setting	1	PSC Setting locked / delayed	

Function code F35, Display Row 1: BBBB

Lock Mode	0*	88888	10 seconds delay
	1	88888	Completely locked
	2	88888	Lock mode depends on keylock Input

Timer

7 Timer

7.1 Timer Description

(Supplementing the General Description in Chapter 4)

Function:

The timer counts seconds, minutes or hours.

Depending on the resolution (see below) the smallest units to be recorded are 0.1 ms

Combined with the prescaler (see below), quantities can be measured as a function of time

Time formats:

4 time formats are available: Seconds, minutes, hours and HH:MM:SS

Resolution:

By shifting the decimal place, a resolution of up to 4 decimal places can be programmed; the smallest resolution is 0,1 ms.

The time format "seconds with four decimal places" shows 0.1 milliseconds. The time format "seconds with three decimal places" shows milliseconds. The time format "minutes with two decimal places" shows 1/100 minutes

Prescaler:

During the timer operation the prescaler has to be disabled or set to 01,0000. The prescaler can be used to record quantities, provided that the quantity per time unit is known.

Example: A volume of 3 liters per second is supplied.
Settings: Time format "seconds", prescaler 3,0000
Display: Supplied volume in liters as a function of time.
The prescaler cannot be used with the time format HH:MM:SS as it is not active (effective) in this format.

Timer mode of operation:

The following modes of timer operation can be selected:

Cumulative measurement following the pulse-width measuring principle (Cumulative measurement as long as input A is active)

Cumulative measurement following the cycle-duration principle

(Cumulative measurement from rising edge Input A to falling edge of Input A)

Cumulative measurement A=Run, B=Stop (cumulative measurement from

rising edge Input A to rising edge Input B)

Single-pulse measurement following the pulse-width measurement principle (Measure as long as Input A is active)

Single-pulse measurement following the cycle-duration principle (Measurement from rising edge Input A to rising edge of Input A)

Single-pulse measurement A=Run, B=Stop (Cumulative measurement from rising edge Input A to rising edge Input B)

Manual Start / Stop via keyboard:

The Start / Stop function can be programmed via the keyboard.

Start: Press the UP button for 0.5s Stop: Press the DOWN button.

Output signals -Function:

A coincidence signal: The timer operates in the "coincidence" mode, i.e. the output signals are enabled for the programmed period of time after reaching the selected preset value

B trail signal: P 2 and P 0 operate in the "coincidence" mode, i.e. the output signals are enabled for the programmed period of time when reaching the selected preset value. P 1 is a trail preset and not absolute to 0, but relative to P

If the setting is F8=1, the following will apply:

Signal 1 is returned at P 2 - P 1

Example: P 2=1000, P 1=200, Signal 1 at 800;

If P1 is negative: P 2=1000, P 1=(-200), Signal 1 at 1200

If the setting is F8=2, the following will be applicable:

Signal 1 is returned at P 2 + und – P 1

(Example: P 2=1000, P 1=200, Signal 1 at 800 or/and 1200)

C range signal: P 1 and 2 are range signals: Signal 1 is active at timer reading < P 1 and

Signal 2 is active at timer reading > P 2

Timer

D batch mode: The timer can also be programmed to act as a batch counter. In this case, P 2= main preset value; P 1= Batch preset.


In the Batch mode of operation, only positive entries are possible for P1; negative entries will be stored as positive values.

This mode is ideal to default a process time and the number of process sequences (runs).


Additional totalizer:

The additional totalizer is used to sum up all the times (even after repeated resetting of the main counter). The totalizer is reset separately.

7.2 Signal Diagrams - Input signals



Timer



7.3 Signal Diagrams - Output signals

The output signals of the timer can be derived from the pulse counter (see 5.3) or, respectively, batch counter (see 9.2) functions.

Timer

Timer

7.4 Programming the Timer function codes

Program- ming mode	Change function setting	Save and change to next function	Return to display mode
E + 🔻	▲ oder ▼		E
Keep pressed and simultaneously turn Voltage On	press	press	press
Alternative display of function codes	+	as text By pressing bot ously you ca numerical disp After pressing again the numl ble options wi addition. Thi	odes are displayed in row 1. In row 1. In keys simultanenchange to the play (F 0 to F 35). In these keys once ber of the selectable displayed in s setting will be ored.

Function code F0, Display Row 1 \pm 2 \pm 5 \pm 8

runction code ro, display now 13 LLLLL				
Function	No.	Display Row 2		
Factory Setting 0* BBBBBB No function (Defaults)				
(,	1	8.8.8.9.8.5.	All function codes are set to the values marked with *	

Function code F1, Display Row 1: 3 A B B B B B

Time unit	0*	988888	Seconds
	1	888888	Minutes
	2	88888	Hours
	3	H.H.B.D.S.S	HH:MM:SS

Function code F2, Display Row 1: 1 5 1 1 1

Resolution	0*	8.8.8.8.8.8.	No decimal point
	1	8.8.8.8.8.	1 decimal place
	2	8.8.8.8.8	2 decimal places
	3	8.8.8.8.8	3 decimal places
	4	8.0.000	4 decimal places

PNP/NPN- Logic			NPN 8 V-Level
	1*	8.0 B _ H =	
	2		
	3	808888	

Function code F4, Display Row 1: R R R E E

Input damping (Attenua- tion)	0	88888	30 Hz damping (attenuation) (e.g. for mechanical contacts)
	1*	H.B.B.B.B.B	F max. (see chapter 4 and 10)

Function code F5, Display Row 15 5 8 8 8

Set / Re- set- Mode	0*	8.6.5 8.8.8.	Reset to 0
	1	888888	Automatic set to 0 after reaching Preset value 2
	2	5.6.6.8.2	Set to Preset 2
	3	858888	Automatically sets to Preset 2 after reaching 0.

Function code F6, Display Row 1: 1 E 5 E E B

dynam/ static Reset	0*	5.8.R.B.B.B.	Static Reset (as long as the signal is applied)
neset	1	898.8.8.	Dynamic Reset (ready to count after reset, even if reset signal is applied for a longer time)

Timer- Mode of Operation	0	888888	Cumulative measurement – pulse- width (counts as long as Input A is active)
	1*	88.8.8.8	Cumulative measurement – cycle du- ration (counts from rising edge of start signal to rising edge of stop sig- nal).
	2	88.8.8.8.5	Cumulative measurement – A=Run B=Stop (counts from rising edge of start sig- nal to rising edge of stop signal).
	3	588888	Single-pulse measurement – pulse- width (counts as long as Input A is active)
	4	5.8.8.8.8.8	Single-pulse measurement – cycle du- ration (counts from rising edge of start signal to rising edge of stop sig- nal).
	5	5.8.8.8.5	Single-pulse measurement - A=Run B=Stop (counts from rising edge of start signal to rising edge of stop sig- nal)

Function code F8, Display Row 1 H E E S B B

Mode Preset 1	0*	8.8.8.8.8.	P 1 normal preset; absolute to counter reading (coincidence signal)
	1	8.8.8.8.8.	P 1 is a trail preset with prefix (relative to P 2)
	2	88888	P 1 as a symmetric trail preset (relative to P 2)
	3	88888	P 1 and P 2 are range signals (Sign.1 <p1, sign.2="">P2)</p1,>

Function code F9, Display Row 1.0 0 E 5 1 0

Output signal		88888	Active On
	1	8.8.8.8.8	

Function code F10, Display Row 1:5 H G H H G

runction code r10, Display Now 1.1111111111			
Signal time P 0	o 885888		Disabled / No output signal
	1	885888	Bistable, reset with Preset 2 or Reset
	2	8.8.8.8.8.	0,02 s
	3	8.8.8.8.8	
	4*	8.8.8.8.8	
	5	8.8.8.8.2	0,20 s
	6	8.8.8.8.58	0,50 s
	7	8.8.8.8.8	
	8	8.8.8.8.8	2,00 s
	9	8.8.8.5.88	
	10	8.8.8.8.8	10,00 s
	11	85666	User setting 1 (0-599,99 s)
	12	8.8.8.8.8.	User setting 2 (0-599,99 s)
	13	8.8.8.8.8.	User setting 3 (0-599,99 s)

Function code F11, Display Row 1:5 🖽 🛱 🖽 🖽

Signal time P 1

0	855860	Disabled / no output signal
1	885888	Bistable, reset with Preset 2 or Reset
2	8.8.8.8.8.2	0,02 s
3	8.8.8.8.8.	0,05 s
4*	8.8.8.8.8	0,10 s
5	8.8.8.8.8	0,20 s
6	8.8.8.8.58	0,50 s
7	8.8.8.8.8	1,00 s
8	8.8.8.8.8	2,00 s
9	8.8.8.5.88	5,00 s
10	8.8.8.8.8	10,00 s
11	85.6.6.6.6	User setting 1 (0-599,99 s)
12	88888	User setting 2 (0-599,99 s)
13	858888	User setting 3 (0-599,99 s)

Function code F12, Display Row 1:5 H L H H E

Signal	
time P	2

0	885868	Disabled / No output signal
1	685686	Bistable; Reset function cannot be used in connection with automatic Reset
2	8.8.8.8.8.2.	0,02 s
3	8.8.8.8.8.5.	0,05 s
4*	8.8.8.8.8.	0,10 s
5	8, 8, 8, 8, 2, 8	0,20 s
6	8.8.8.8.6.5.8	0,50 s
7	8, 8, 8, 8, 8, 8.	1,00 s
8	8.8.8.2.8.8	2,00 s
9	8.8.8.5.8.8.	5,00 s
10	8.8.8.8.8.8	10,00 s
11	858888	User setting 1 (0-599,99 s)
12	8.5.6.6.8.2	User setting 2 (0-599,99 s)
13	856688	User setting 3 (0-599,99 s)

Function code F13, Display Row 1988 888

Stop after reaching		8.8.8.8.8	No Stop when main Preset is reached (P 2)
the main Preset	1	8.8.8.9.8.5.	Stop when main Preset is reached (P 2)

Function code F14, Display Row 1: BBBBB

Display flashes	0*	0.6.6.0.5.H	no flashing
	1	8.8.8.8.8.	Flashes as long as P 0 is active
	2	8.8.8.8 . 8.	Flashes as long as P 1 is active
	3	8.8.8.8. 8.2 .	Flashes as long as P 2 is active
	4	8.0.8.8.8.8.	Flashes as long as 1 P is active

Function code F15, Display Row 1:2. 4 4 5 5

Display in 2nd Row	0	8.8.8.8.8.	Preset 0
	1	8.8.8. 8. 8.	Preset 1
	2*	8.8.8.8. 8.2 .	Preset 2
	3	8.8.8.8.6.	Prescaler
	4	6.6.6.R.E	Totalizer / Batchcounter

Function code F16, Display Row 188888

Start / Stop via Keyboard	0*	885888	Start / Stop locked via keys UP key=Start; DOWN key = Stop
(manual)	1	888888	Start / Stop enabled via keys UP key =Start; DOWN key =Stop

Function code F17, Display Row 1: 8 8 8 8 8

Power On Reset	0*	Restore counter value
	1	Reset at Power On

Function code F18, Display Row 1 🖁 🖁 🖁 🖁 🖁



Function code F19, Display Row 1: H d d b a b

Addtl. Totalizer	0	8.8.8.98.5	Enabled	
		888888		

Function code F20, Display Row 1:8 8 8 8 8

Prescaler

O* BBBBB Prescaler not active

1 EBBBB Prescaler active

Timer Type

0* EBREAB Preset timer

1 BREAH Batch timer

Function code F22, Display Row 1: 1888

Application
Output

1* PIRBE Run-Input

2 SEBRE Stop-Input

3 FESRE Reset counter and totalizer or batch counter

4 FESERE Reset – only counter

5	8.8.5.8.8.8	Reset - only totalizer or batch counter
6	8.8 8.8.8.8.	Keylock input
7	888888	Hold input (display memory)
8	888888	Teach Input (count value becomes P 2)
9	5 9 8 8 8 8 8	Set Input (set to Preset 0)



Should you have a counter with interface, the additional function codes F24 - F27 are described in the seperate manual for the interface version.

Function code F30, Display Row 1 🖥 🖁 🖥 🖥 🗸

Lock Reset Key			Keyboard reset enabled
	1	8.8.8.8.8.8.	Keyboard reset locked / delayed

Function code F31, Display Row 1: \square \square \square \square \square \square \square \square \square

tina			P 0 Setting enabled
	1	8.8.8.8.8.8.	P 0 Setting locked / delayed

Lock Pre- set 1 Set- ting	0*	 P 1 Setting enabled	
ting	1	P 1 Setting locked / delayed	

Function code F33, Display Row 19 2 2 2 2

Lock Pre- set 2 Set-	0*	P 2 Setting enabled
ting	1	P 2 Setting locked / delayed

Function code F34, Display Row 1 # 5 8 8 8 8

Lock Pres- caler Set-	0*	8.8.8.8.8.	PSC Setting enabled
ting	1	8.8.8.8.8.8.	PSC Setting locked / delayed

Lock Mode	0*	888888	10 seconds delay
	1	8.8.88.8.8	Completely locked
	2	88888	Lock mode depends on keylock input

8 Shift Counter

8.1 Shift Counter Description

(Supplementing the general description under chapter 4)

Function:

2-shift counters enable the acquisition of 2 separate partial sums.

Counter input A acts on partial sum 1, whereas counter input B acts on partial sum 2.

Both partial sums are counted positively; the total sum is calculated mathematically and corresponds to the summed-up total (or respectively, the difference) of the partial sums.

The total sum remains unchanged after resetting one of the partial sums.

Counter mode of operation:

The following counter modes of operation can be selected: Difference counting and summation (totalizing)

Output signals - mode of operation:

The counter operates in the "coincidence" mode, i.e. the output signals are enabled for the programmed period of time after reaching the selected Preset value.

The total sum acts on Preset 0 Partial sum 1 acts on Preset 1

Partial sum 2 acts on Preset 2

Reset:

After a reset at input C, both partial sums and the total sum are reset. When resetting via the application input it is possible to reset one or both of the partial sums or the total sum, depending on the selected programming. When resetting via the keyboard, only the value shown on the display is reset.


Totalizer:

The totalizer sums up all the input pulses, even if the partial sums and the total sum are reset. The totalizer can only be reset manually.

Shift Counter


8.2 Scrolling between Total Sum and Partial Sums


The Shift key is used to scroll between the total sum and partial sums 1 and 2.



If a partial sum is shown, SU1 or SU2 will appear flashing in the lower display bar.

8.3 Signal diagrams - Inputs (PNP Logic)





8.4 Signal Diagrams - Output signals

Output signals - monostable
Coincidence signals P 0/Total Sum (F10), P 1/Partial sum 1 (F11), P 2/Partial sum 2 (F12) monostable

Counter reading	Preset 1 Partial sum1	Preset 2 Partial sum 2	Preset 0 Total sum
P 1 (Relay)	Signal time		
P 2 (Relay)		Signal time	
P 0 electronic			Signal time
(Application output)			
P 1 electronic	Signal time	Signal	
P 2 electronic		time	

Shift Counter

Shift Counter

8.5 Programming the Shift Counter Function Codes

Programming mode	Change func- tion setting	Save and change to next function	Return to dis- play mode
E + 🕶	▲ or ▼		Е
Keep pressed and simultaneously turn Voltage On	press	press	press
Alternative dis- play of Function codes	+	The function codes text in row 1. By prosimultaneously you the numerical display. After pressing these the number of the stions will be display. This setting will be	essing both keys can change to ay (F 0 to F 35). e keys once again selectable opered in addition.

Function code FO, Display Row 1 \(\frac{1}{2} \) \(\frac{1}2 \) \(\frac{1}2 \) \(\frac{1}2 \) \(\

Function	No.	Display Row 2	
Factory Setting (Defaults)	0*	8.8.8.8.8.	No function
	1	8.8.8.8.8.5.	All function codes are set to the values marked with *

Function code F1, Display Row 1: 4 4 4 5 5

			Input A	Input B	Input C
Counter mode of Operation	0	R.B.S.B.B.B.	Adding	Subtracting	Reset
	1*	88888	Adding	Adding	Reset

Function code F3, Display Row 1: H H H L D D

Tunction	Tunetion code 13, Display Now 1.1. The E E E				
PNP/ NPN-Lo- gic	0		NPN 8 V-Level		
	1*	P888H8	PNP 8 V-Level		
	2				
	3	888888			

Function code F4, Display Row 1: 3 - 8 - 8 - 5

Input	0	88888	30 Hz damping (attenuation); e.g. for mechanical contacts
Attenuat.	1*	88888	F max. (see chapter 4 and 10)

Function code F5, Display Row 1986 8

With / without O BBBBB With Preset

1* BBBBB BB Without Preset

Function code F6, Display Row 15 E5 EE 8

Dynamic/	0*	5 E.A E.B.B.	Static reset (reset as long as signal is applied)
static Reset	1	898888	Dynamic Reset (ready to count after reset, even if reset signal is applied for a longer time)

Function code F9, Display Row 1 🖁 🖥 🖺 🖫 🖫

Output signal	0*	ABBBBA	Active On
	1	8.8.8.8.8.	

Function code F10, Display Row 1:5 1 1 1 1 1 1

Signal time P 0 Total	0		Disabled / no output signal
		885888	Bistable; reset with Reset
Sum		8.8.8.0.02	
		8.8.8.8.8.8	
		8.8.8.8.8.	
		8.8.8.8.28	
		8.8.8.8.8.	
		B. B. B. B. B. O.	
		8.8.8.8.8.8	
	9	8.8.8.5.00	
		8.8.8.0.0.0	

858888

856666

User setting 1 (0-599,99 s)

User setting 2 (0-599,99 s)

User setting 3 (0-599,99 s)

Function code F11, Display Row 1:5 8 6 8 8 8

Signal time P 1 Partial sum 1

0	885888	Disabled / no output signal
1	685886	Bistable; reset with Reset
2	8.8.8.0.0.2.	0,02 s
3	8.8.8.8.8.5	0,05 s
4*	8.8.8.0.8.0.	0,10 s
5	8.8.8.8.20	0,20 s
6	8.8.8.0.5.0.	0,50 s
7	8.8.8.8.8.8	1,00 s
8	8.8.8.2.0.0	2,00 s
9	8.8.8.5.0.0	5,00 s
10	8.8.8.0.0.0	10,00 s
11	858888	User setting 1 (0-599,99 s)
12	8.5.6.6.6.2.	User setting 2 (0-599,99 s)
13	8.6.6.6.6.6.	User setting 3 (0–599,99 s)

Function code F12, Display Row 1:5 8 8 8 8

Signal time P 2 Partial sum 2

	0	885888	Disabled / no output signal
	1	685886	Bistable; reset with Reset
	2	8.8.8.8.8.2	0,02 s
	3	8.8.8.8.8.5	0,05 s
	4*	8.8.8.8.8.	0,10 s
	5	8.8.8.8.8.	0,20 s
	6	8.8.8.8.5.8	0,50 s
	7	8.8.8.8.8.8	1,00 s
	8	8.8.8.2.00	2,00 s
	9	8.8.8.5.00	5,00 s
	10	8.8.8.0.00	10,00 s
	11	858888	User-Einstellung 1 (0-599,99 s)
	12	8.5.8.8.8.	User-Einstellung 2 (0–599,99 s)
	13	888888	User-Einstellung 3 (0-599,99 s)

Function code F13, Display Row 1:3 8 8 8 8 8

Decimal Point	0*	8.8.8.8.8.8.	No decimal point
	1	8.8.8.8.8.	1 decimal place
	2	8.8.8.8.8	2 decimal places
	3	8.8.8.8.8	3 decimal places
	4	8.8888	4 decimal places

Function code F14, Display Row 1: EE H S H

Function code F15, Display Row 1:2. 2 2 3 5

		. , ,	
Display in 2nd Row	0	8.8.8.8 .8 .	Preset 0
	1	8.8.8.8.8.	Preset 1
	2*	8.8.8.8.8.2.	Preset 2
	3	8.8.8.8.8.	Prescaler
	4	8.8.8.5.8.	Partial sum 1
	5	8.8.8.8.8.	Partial sum 2
	6	8.8.8.8.8.	Totalizer

Function code F17, Display Row 1800 8

Power-On Reset	0*	Restores the counter value
	1	 Reset at Power On

Output	o 8.8.8.985.		Restart signal time after power fail output switches	
Signal Memory	1*	8.8.8.8.8.	Do not restart signal time after power fail	

Addtl. Totalizer	0	8.8.8.9.8.5.	Additional totalizer is enabled
	• • • • • • • • • • • • • • • • • • • •	••••	•
TOTATIZET	1*	8.8.8.8.8.8	No additional totalizer

Function of

8.8.8.8.8.

Application Input/ Output

code l	- -22, Display Rov	v 1.888808
0	8.08.08.8	Output Preset value 0
1*	828888	2nd counter input partial sum 1
2		2nd counter input partial sum 2
3		Reset of partial sum 1
4	8.8.5.8.5.8.	Reset of partial sum 2
5	8.8.5.5.8.2.	Reset of both partial sums
6	888888	Reset of total sum
7	H = E = E = E	Hold Input (display memory)



Should you have a counter with interface, the additional function codes F24 - F27 are described in the seperate manual for the interface version.

Function code F30, Display Row 1 1 8 8 8 8 8

Lock Reset key	0*	88888	Keyboard reset enabled
	1	8.8.8.8.8.8	Keyboard reset locked / delayed

Function code F31, Display Row 1: \square \square \square \square \square \square \square \square \square

	0*		P O Setting enabled
Lock Preset 0	1	8.8.8.8.8.	P O Setting locked / delayed

Function code F32, Display Row 1 🖁 🗎 🖥 🖥 🗸

Lock	0*	88888	P 1 Setting enabled
Preset 1	1	8.8.8.8.8.8.	P 1 Setting locked / delayed

9

Keylock Input

Function code F33, Display Row 19 2 2 2 2

Function code F34, Display Row 1: 95 1 2 2



Function code F35, Display Row 1: BBBB

Lock Mode	0*	888888	10 seconds delay	
	1	8.8.8 8.8.8	Completely locked	
	2	888888	Lock mode depends on keylock input	

9 Batch Counter

9.1 Batch Counter Description

(Supplementing the general description in Chapter 4)

Function:

Preset 2 is the main Preset setting.

Preset 1 is the Batch Preset or, respectively, the preset value of the 2nd totalizer

In the batch operation the batch counter counts how often the main Preset is activated.

Example of an application: during length cutting operations, for example, both the lengths (main preset) and number (batch preset) can be monitored. In the Batch mode of operation, only positive entries are possible for P1; negative entries will be stored as positive values.

Counter mode of operation:

The following modes of operation can be adjusted for the counter: Unidirectional counting, adding or subtracting:

Unidirectional counting, adding or subtracting;

Difference counting, summation and phase discrimination (quad) with single, double or quadruple evaluation.

Output signals Mode of Operation:

The counter operates in the coincidence mode, i.e. the output signals are enabled for the programmed duration when the selected preset value is reached.

Prescaler Output PSC-out:

The Prescaler output is an application output.

With each increase of the counter reading the number of output pulses corresponds to the respective number of increments.

The pulse length of the prescaler output corresponds to a frequency of 500 Hz. When using the prescaler output the max. input frequency is:


 $F \max = 500 / PSC.$

So it is possible that the maximum input frequency can not be reached.

Batch Counter

Batch Counter

Signal Diagrams - Inputs and Outputs



Programming the Batch Counter Function Codes

Programming mode	Change function setting	Save and change to next function	Return to dis- play mode
E ₊ ▼	▲ or ▼		Е
Keep pressed and simultaneously turn Voltage On	press	press	press
Alternative display of Function codes		The function cod as text i By pressing both ously you can ch merical display (F pressing these ker number of the se will be displayed setting will	n row 1. keys simultane- lange to the nu- 0 to F 35). After ys once again the electable options in addition. This

Function code FO, Display Row 1: E E E E E

Function	No.	Display Row 2	
Factory Setting (Defaults)	0*	8.8.8.8.8	No function
	1	8.8.8.9 8.5.	All function codes are set to the values marked with *

Function code F1, Display Row 1 🗄 🗎 🖺 🗒 🗎

Counter Mode of Operation	0*	0.0.0.0.0.0.0.	Input A	Input B	Input C
			Count Input	Gate	Reset
	1	9 . 8. 8. 8. 9 . 8.	Count Input	Directional input	Reset
	2	8.8.8.8.6.8.	Count Input	Directional input	Gate
	3	8.8.5.8.8.8.	Adding	Subtracting	Reset
	4	8.8.5.8.6.8.	Adding	Subtracting	Gate
	5	8.8.8.8.8.	Adding	Adding	Reset
	6	98888	Channel A	Channel B	Reset
	7	9.888.6	Channel A	:	Gate
				115110	

Function code F2, Display Row 1:93888

Edge Evalua- tion Quadrat. Evalua-	0*	8.8.8.8.8.	Single evaluation
	1	8.8.8.8.8.	Double evaluation
tion	2	8.8.8.8.B. H .	Quadruple evaluation

Function code F3, Display Row 1: \Box \Box \Box \Box \Box

PNP/ NPN-Lo- gic	0	080948	NPN 8 V-Level
	1*	PRPLH	
	2	888888	
	3	888888	PNP TTL-Level

Function code F4, Display Row 1: 3 7 8 8 8

Input damping	0	88888	30 Hz damping (e.g. for mechanical contacts)
(At- tenuat)	1*	88888	F max. (see chapter 4 and 10)

Function code F5, Display Row 1 4 5 8 8 8 8

Set / Re- set- Mode	0*	885808	Reset to 0
	1	88888	Automatic reset to 0 when Preset value 2 is reached
	2 58882		Sets to Preset value 2
	3	858888	Automatic set to Preset 2 after reaching 0

Function code F6, Display Row 1: 8 5 5 6 8 8

Dynamic/	0*	588888	Static Reset (reset as long signal is applied)
static Reset	1	888888	Dynamic Reset (ready to count after reset, even if reset signal is applied for a longer time)

0	0*	888888	Active On
Output signal			
	1	866088	Active Off

Function code F10, Display Row 1:5 🗄 🖟 🗎 🗗

Signal	
time P	0

0	885868	Disabled / no output signal
1	88.58.88	Bistable; reset with Preset 2 or Reset
2	8.8.8.8.8.	0,02 s
3	8.8.8.8.8.5	0,05 s
4*	8.8.8.8.8	0,10 s
5	8.8.8.8.8	0,20 s
6	8.8.8.8.58	0,50 s
7	8.8.8.8.8	1,00 s
8	8.8.8.2.88	2,00 s
9	8.8.8.5.88	5,00 s
10	8.8.8 8.8 8	10,00 s
11	85.88.8.8	User-setting 1 (0–599,99 s)
12	888888	User-setting 2 (0–599,99 s)
13	858888	User-setting 3 (0-599,99 s)

Function code F11, Display Row 1:5 8 8 8 8

Signal time P 1 Batch-Preset

0	885888	Disabled / no output signal
1	685686	Bistable; reset with Reset
2	8.8.8.8.8	0,02 s
3	8.8.8.8.8.5	0,05 s
4*	8.8.8.8.8	0,10 s
5	8.8.8.8.8	0,20 s
6	8.8.8.8.58	0,50 s
7	8.8.8.8.8	1,00 s
8	8.8.8.8.8	2,00 s
9	8.8.8.5.88	5,00 s
10	8.8.8.8.8	10,00 s
11	858888	User-setting 1 (0-599,99 s)
12	8.5.6.6.6.6.	User-setting 2 (0-599,99 s)
13	858888	User-setting 3 (0-599,99 s)

Function code F12, Display Row 1:5 1 1 1 2

Signa	al	
time	Р	2

0	885868	Disabled / no output signal
1	685886	Bistable; reset with Reset Cannot be used in connection with automatic Reset
2	8.8.8.8.8	0,02 s
3	8.8.8.8.8.8	0,05 s
4*	8.8.8. 8. 8.8	0,10 s
5	8.8.8.8.8.8	0,20 s
6	8.8.8. 8.8 .	0,50 s
7	8. 8. 8. 8. 8 . 8 .	1,00 s
8	8.8.8.2.8.8	2,00 s
9	8.8.8.5.8.8	5,00 s
10	8.8.8.8.8.8.	10,00 s
11	8.5.8.8.8.8	User-setting 1 (0-599,99 s)
12	858888	User-setting 2 (0-599,99 s)
13	88888	User-setting 3 (0-599,99 s)

Function code F13, Display Row 1: 4 P a R a E

Decimal point	0*	8.8.8.8. 8 .	No decimal point
	1	8.8.8.8.8	1 decimal place
	2	8.8.8.8.8	2 decimal places
	3	8.8.8.88	3 decimal places
	4	88888	4 decimal places

Function code F14, Display Row 1: BBBB

Display flashes	0*	88888	No flashing
	1	8.8.8.8.8.8	Flashes as long as P 0 is active
	2	8.8.8. 8 .8	Flashes as long as P 1 is active
	3	8.8.8.8.8	Flashes as long as P 2 is active
	4	8.0.8.8.8.8	Flashes as long as one Preset is active

Function code F15, Display Row 1.2. 8 8 8 8

Display in 2nd row	0	8.8.8.8 .8 .	Preset 0
	1	8.8.8.8 .8 .8.	Preset 1
	2*	8.8.8.8.8.8	
	3	8.8.8.8.8.8	
	4	686850	Batch counter or 2nd counter

Function code F16, Display Row 1: E = E E E E

External Reset signal	0		Only resets the counter
	1	0.85688	Only resets the batch counter
	2*	8.8.8.8.8.8	Resets all counters

Function code F17, Display Row 1800 5

Power On Reset	0*	0.6.8.8.8.5.	Restores the counter value
	1		Reset at Power On

Function code F18, Display Row 1888

Output signal- Memory	o 8.8.89E5		Restart signal time after power fail Output switches
	1*	8.8.8.8.8	Do not restart signal time after po- wer fail

Function code F19, Display Row 1: HH HH

Batch- Counter	0*	686686	Batch counter
or 2nd totalizer	1	2.8.0.8.8.8.	2nd totalizer

Function code F22, Display Row 1 H R L H R

Applica- tion in-	0	P5000E	Prescaler output
put/	• • • • • • •	••••••	•••••••••••
output	1	P0 0 E	Output Preset 0
			. .

Should you have a counter with interface, the additional function codes F24 - F27 are described in the seperate manual for the interface version.

Function code F30, Display Row 15 5 5 5 5 5

Lock Re- set key	0*	888888	Keyboard reset enabled
	1	8.8.8.8.8	Keyboard reset locked / delayed

Function code F31, Display F	Row 1:8 8 8 8 8 8
------------------------------	-------------------

Lock	0*		P 0 Setting enabled
Preset 0	•••••		•••••••••••••••••••••••••••••••••••••••
Setting	1	8.8.8.8.8.8.	P 0 Setting locked / delayed

Function code F32, Display Row 1: 8 8 8 8 8

Lock	0*	8.8.8.8.8.8.	P 1 Setting enabled
Preset 1	•••••	•••••	•••••
Setting	1	8.8.8.8.8.8.	P 1 Setting locked / delayed

2	888888	Directional count output
3*		Count input, adding
4	888888	
5	885888	Reset counter and Batch counter or 2nd totalizer
6	888888	Resets only counter
7	888888	Resets only Batch counter or 2nd totalizer
8	888888	
9	8 8.8.8.8.	Keylock input
10	H B B B B B	Hold input (display memory)
11	888888	Teach input Count value becomes P 2
12	58.8.8.8.8.	Set-input (sets to Preset 0)

Batch Counter Technical Data

Function code F33, Display Row 1 8 2 8 8 8

Lock	0*	88888	P 2 Setting enabled
Preset 2 Setting		888888	P 2 Setting locked / delayed
-			r 2 Setting locked / delayed

Function code F34, Display Row 1:85 1 8 8

Lock	0*	8.8.8.8.8.8.	PSC Setting enabled
Prescaler Setting			PSC Setting locked / delayed

Function code F35, Display Row 1: 4 8 8 8 8

Lock Mode	0*	888588	10 seconds delay	
	1	8.8.8 8.8.8	Completely locked	
	2	88888	Lock mode depends on Keylock input	

10 Technical Data

General

Display LCD reflective,

Transflective positiv: black figures on back lighted ground Transmissive negativ: white, red or green figures on black ground 2 lines, counter reading/presettings 6-digits; deci-

mal point (up to 4 decimals)

Digit hight 1st line 9.3 mm; 2nd line 7.2 mm

View angle 12 o'clock

Supply voltage SELV: 12-30 VDC; protected against polarity reversal

SELV: 24 VAC, 50/60 Hz, ± 10%

115 VAC; 230 VAC, 50/60 Hz, ± 10% 100-240 VAC; 50/60 Hz, ± 10%

Current consump-

tion

12 ... 30 VDC < 200 mA,

12 - 30 VDC with backlight < 250 mA incl. sensor supply

24 VAC < 250 mA; including sensor supply 115/230 VAC < 50 mA; incl. sensor supply

100 - 240 VAC < 80 mA at 90 VAC; incl. sensor supply

Power consumption < 5 W

< 8 W switching power supply

Duty cycle 100%

Overload protection external fuse DC: 0,16 AT (IEC 127); DC: 0,2 AT (UL 198)

24 VAC: 315 mAT; 230 VAC: 32 mAT; 115 VAC: 63 mA T

100 - 240 VAC G-safety insert 630 mA/250V

Overload protection Relay output

external fuse 230 V, 2,5 A mT

Sensor supply 24/115/230 VAC

AC-operation: 12-24 VDC (load dependent), max. 50 mA

90-260 VAC (switching power supply) AC-operation: 24VDC/-5%, max. 115 mA

max. capacitive load = 470 μ F

Technical Data

Storage of values NV-memory > 10 years

Electrical connec-Plug-in screw-type connections / Terminals

tions

Cable cross-section 1 15 mm² with wire-end sleeves

Amplitude threshold < 2 V and > 8 V or < 1 V and > 4 V at TTL-level amplitude

max. 40 VDC

Active edge programmable positive for PNP-input.

negativ for NPN-input

Input resistance approx. 10 kOhm

Count frequency max. 60 kHz (TTL 20 kHz): single-channel counting

> Different, counting and totamax. 60 kHz (TTL 20 kHz):

lizing channel (A+B together)

max. 30 kHz (TTL 20 kHz): phase discriminator single or

double evaluation

max. 15 kHz (TTL 15 kHz): phase discriminator, quadruple

evaluation

damped (attenuated) 30 Hz

-> Please pay attention to graphics on page 117

Pulse form any desired form (at max. frequency square 1:1)

Pulse duration min 17 ms (30 Hz); 8 μs (60 kHz)

Prescaler 0,0001 - 99,9999

manual reset via keyboard Reset

> external reset static or dynamic programmable pulse length min. 5 ms. automatic reset after reaching Preset 2, (No pulse losses at max. counter frequency due

to automatic reset function).

via application input (programmable) and

programmable Power-On Reset

Setting to Preset 0 (independent of reset) Set function

Display and Preset

- 999 999 up to + 999 999

Range

Technical Data

Warning signal Display flashes when preset 0. 1 or 2 are active

Signal times 0.01 s to 599.99 s or bistable programmable

> tolerance + 10ms active On or Off

Relay Output Change-over contact max, 250 VAC / 30 VDC / 5 A for P 1 and P 2 Change-over contact min. 5 VAC / 5 VDC / 10 mA

> delay < 10 ms PNP-output

Transistor Output for P 1 and P 2

12 - 30 VDC max. 50 mA at DC-supply

12 - 24 VDC max. 30 mA at AC-supply (24/115/230 VAC) 24 VDC, max 50 mA at AC-supply with switching power

supply

Application Output PNP-output

12 - 30 VDC max, 20 mA at DC supply

12 - 24 VDC max. 20 mA at AC supply (24/115/230 VAC) 24 VDC max. 20 mA at AC-supply with switching power

supply



Only for trafo-power-supply:

Current load of the outputs (Sensor 12-24 VDC, Out 1, Out 2, Application-Output) is not allowed to exceed 65 mA in sum.

Counter

Application In-

put/Output

Counter mode of Unidirectional; adding or subtracting; directional input; Differential operation, add / sub: Summation (Totalizing) operation Input A.B add / add: Phase discriminator single, double or quadruple

evaluation

Control Input Reset: Gate

Preselect Mode Absolute or trail, Range signal /limit values (sign. 1 < P1,

113

sign. 2 > P 2

Output: Prescaler-out, Preset 0-out, Direction-out addtl. counter input add / sub, Reset, Set,

Gate, Keylock, Hold, Teach in

Technical Data

Batch Counter	
Mode	Batch counter with Preset or 2nd totalizer with Preset
Shift Counter	
Counter Mode of Operation	Differential counting add/sub, totalizing add/add

of Operation				
Tachometer				
Measuring Principle	Period (cycle) measurement (1/Tau)			
Time base	1/min or 1/s			
Min. frequency	1 Hz or 0,1 Hz			
Limit values pression	2 alarms with programmable startup sup +1 additional upper limit value on the application output			
Tachometer mode of operation	Unidirectional add oder sub; directional input;Differential add / sub; totalizing add / add; Phase discriminator single, double or quadruple evaluation, A / B or (A-B) / A %			
Application Input/Output	Output: Preselect 0-out, Direction-out Input: addtl. counter input add / sub, Keylock, Hold, Teach in			
Accuracy of the tachometer function	Time base: \pm 30 ppm Measuring principle: Periodic measurement Measuring time: min. 0,5s / max. 1s oder 10s Measuring resolution: 0,4 μ s(<30 ppm) Display resolution: 4 decimal places, 1 Digit = 100 ppm			
Overall tolerance	= Shown resolution + tolerance of timebase = 130 ppm			

Technical Data

Timer			
Measuring Principle	Pulse-width or cycle duration measurement Start Inp. A + Stop Inp. B; Start/Stop key		
Time base	Programmable in sec, min, h or hh.mm.ss		
Resolution	1; 0,1; 0,01; 0,001; 0,0001		
Function	Single-pulse or cumulative measurement		
Application In- put/Output	Output: Preselect 0-out Input: addlt. Run, Stop, Reset, Set, Keylock, Hold, Teach in		
Accuracy of the timer	Time base: ± 30 ppm Start / Stop-point in time: 16 µs / 16 ms (not damped / damped) Resolution: 100 µs = 100 ppm		
Overall tolerance	= Shown resolution + tolerance of timebase = 130 ppm		

Environmental conditions / Safety Rules

	- ,
General design	EN 61010-1 / IEC 61010-1
Protection Class	II; EN 61010-1 / IEC 61010-1
Pollution degree	V 2, EN 50178
EMC - Interference immunity	EN 61326-1 industrial environment *
EMC - Emission	EN 61326-1 Class B *
Ambient tem- perature	0° 50°C EN 60 068-2-1/2 0° 45°C with block assembly 0° 50°C in single row assembly
Storage tem- perature	- 20° + 65°C EN 60 068-2-1/2
Climate	40°C / 93% rel hum. class 4K4H, EN 60 068-2-78 25 - 50°C / 93% rel hum., cyclic, EN 60 068-2-38
Altitude	up to 2000m

Technical Data Technical Data

Degree of pro- IP 65 front side; EN 60529

tection IP 20 terminals

Vibration resistance 10 m/s² (10 ... 150 Hz); EN 60 068-2-6

Shock resistance 100 m/s² (18 ms); EN 60 068-2-27

Resistence to

Frontfoil acc. to DIN 42 115-2

chemicals

Approvals UL, CSA: E 338588

RoHS compliant

Mechanical Data

Installation Front-panel installation with tenter (frame) Front panel


thickness max. 11 mm


Dimensions 48 mm x 48 mm x 118 mm, installation depth 110 mm

DIN 43700

Front-panel cutout 45 mm x 45 mm + 0,3 mm

Weight approx. 200 g





^{*} For cable length > 30 m, for connection to a DC-supply-network and input level TIL an additional protection circuit is necessary.

Transport, Packaging, Storage

11 Transport, Packaging, Storage



Note! Damage may be caused by improper transport! Improper transport may cause considerable damage. Do not remove the packaging before assembly and installation.

The packaging offers ideal protection against mechanical damage and loss of single parts, such as the plugs or operating instructions. Therefore, do not take the multifunctional counter out of its packaging until you actually have to start your assembly and installation work.

Inspect the shipment for completeness and possible signs of transport damage immediately after receipt.

12 Maintenance and cleaning

The multifunctional counter does not require any maintenance.

The front side may be cleaned with commercially available household detergents.

For protection against pollution, a transparent, flexible protection cover is available as accessory (see chapter 17). With this protection cover, the counter display can be read and the buttons can be used.

13 Malfunctions



Warning!

Danger of injuries due to improper fault correction! Improper fault correction may cause serious damage or personal injury.

The machine/plant manufacturer is responsible for the preparation of operating instructions or a description stating the potential errors and the appropriate corrective action, as well as potential hazards and the behavior in the event of malfunctions. This is dependent on the design concept and construction of the machine or plant.

The first step is to determine if the cause of an error or malfunction implies a possible fault of the multifunction counter.

Overview of Errors

Error	Possible cause	To be corrected by:	
Display re- mains dark	Machine/plant not powered on	Operator	
	Defective voltage supply	Qualified electrician	
Value is not stored	Power-on reset is active (F17)	Skilled personnel	
Counter/ tachometer does not count	Defective signal generator; Counter does not receive any counting signals	Skilled personnel	
	Adjusted to incorrect mode of operation (F1), Single-channel, directional input, differential counting, phase discriminator	Skilled personnel	
	Incorrect adjustment of PNP/NPN logic and input level (F3)	Skilled personnel	

Malfunctions

	High-level does not exceed the up- per amplitude threshold; low-level does not fall below the lower amp- litude threshold	Qualified electrician	
	Continuous reset signal is applied	Qualified electrician	
	Continuous gate signal is applied	Qualified electrician	
Incorrect	Prescaler value is not correct	Skilled personnel	
counting of counter/ tachometer	Phase discriminator - edge evaluation not correctly adjusted (F2)	Skilled personnel	
	Input frequency too high (F4)	Skilled personnel	
Keyboard Reset not possible	Keys are locked (F30 + F35)	Skilled personnel	
Presetting not possible	Keys are locked (F31, F32, F33 + F35)	Skilled personnel	
Prescaler ad- justment not possible	Keys are locked (F34+ F35)	Skilled personnel	
Signal 0, 1 or 2 not received	Signal deactivated (F10, F11, F12)	Skilled personnel	
	User signal time adjusted to 0,000	Skilled personnel	

Spare Parts / Dismantling and Disposal

14 Spare Parts



Warning! Danger due to faulty spare parts!

The use of incorrect or faulty spare parts may cause damage, malfunction or even total breakdown and safety hazards. Therefore, please make sure only to use the original spare parts provided by the manufacturer.

The multifunctional counter may only be opened by the manufacturer. Exclusively outer components are available as spare parts.

The order numbers are given in Chapter 17.

15 Dismantling and Disposal

After reaching the end of its useful life the multifunctional counter has to be disposed of or recycled according to the applicable environmental protection rules.

HENGSTLER 120 121 HENGSTLEI

Ordering Information

16 Ordering Information

Display LCD	Relay	12-30 VDC	24 VAC	115 VAC	230 VAC	100-240 VAC
reflective	1	0 772 101	0 772 111	0 772 121	0 772 131	0 772 141
reflective	2	0 772 102	0 772 112	0 772 122	0 772 132	0 772 142
transflective positive	1	0 772 201	-	-	-	0 772 241
transflective positive	2	0 772 202	-	-	-	0 772 242
transmissive white	1	0 772 301	-	-	-	0 772 341
transmissive white	2	0 772 302	-	-	-	0 772 342
transmissive red	1	0 772 401	-	-	-	0 772 441
transmissive red	2	0 772 402	-	-	-	0 772 442
transmissive green	1	0 772 501	-	-	-	0 772 541
transmissive green	2	0 772 502	_	-	-	0 772 542

Reflective: black figures on bright reflecting background

Transflective positive: black figures on back lighted ground Transmissive white: white figures on black ground red figures on black ground Transmissive green: green figures on black ground

Accessories

17 Accessories

Adapter front pand Order no.	el Dimensions	Front panel cutout
1 405 675	60 x 75 mm	55 x 55 mm
1 405 676	72 x 72 mm	68 x 68 mm
1 405 679	125 x 60 mm	106 x 55 mm for installation of 2 counters 48 x 48
protection cover	2 772 052	
(tenter) frame	1 721 004	48 x 48 mm

HENGSTLER 122 123 HENGSTLER



HENGSTLER

Hengstler GmbH | Uhlandstr. 49 | 78554 Aldingen Telefon +49 (0) 7424-890 | info@hengstler.com www.hengstler.com